

634 Series

4 Amp Power Controllers



Access control system power requirements are uniquely different from other systems. Unlike camera system power requirements, access control systems draw more current for locking hardware and during access control-related events. 75 – 85% of access control operating problems and technical support calls are due to power issues.* Access control systems require steady and clean (filtered) low-voltage DC current with surge suppression to protect printed circuit boards and connected devices from damage due to dirty power (transients and voltage spikes).

SDC power supplies have been developed specifically to help reduce power system issues and to support electric locks and access control requirements. Our hybrid design combines the efficiency of switching power supplies with the inductive load handling capability of linear power supplies in various 12/24 VDC current output capabilities and enclosure sizes. Filtering and output voltage regulation provide protection and ensure the longevity of all system components.

The high performance, heavy-duty circuitry is ideal for inductive loads and multi-door applications. With the addition of SDC programmable controllers or relay modules, the user-friendly modular designs ensure versatility, interface capability and easy installation of virtually any electric locking devices, access controls and related fire & life safety equipment.

* SDC technical support logs.



MODELS

634RFA 4 Amp DC Power Controller With Large Cabinet



STANDARD FEATURES

- Regulated and filtered linear DC power
- Class 2 outputs
- Field selectable dual voltage
- Fire/emergency release input
- Isolated battery charging circuit
- Low battery disconnect
- Input and output surge protection
- Troubleshooting visual status indicators (LED)
- Cabinet enclosures with pre-configured control module mounting holes



OPTIONAL FEATURES

- 230 VAC, 50/60 Hz input
- Cover visual status indicator (LED)
- Key lock cover
- Fire/emergency release manual reset switch
- System on/off switches
- Choice of compatible door control modules



APPLICATIONS

ISOLATED BATTERY CHARGING CIRCUIT

A separate charging output provides 13.5 or 27 volts to fully charge the batteries. The secondary output is always precisely maintained at 12 or 24VDC to protect locking devices and components from over voltage while the batteries are charging. The specified secondary output current is also maintained while batteries are charging. Derating of the secondary output current is not required when charging batteries.

LOW BATTERY DISCONNECT

Batteries are disconnected from the output circuit prior to deep discharge preventing battery destruction. Batteries are not included and should be ordered separately.*

INPUT & OUTPUT SURGE PROTECTION

Input and output surge protection is built-in. The AC input voltage is circuit breaker protected and the outputs are PTC protected.

TROUBLESHOOTING VISUAL STATUS INDICATORS (LED)

LED visual status indicators are included on the board to provide information regarding the AC input, DC output and battery backup status.

INTERNATIONAL STANDARD INPUT

An alternative 230VAC international standard input is an available option.

COVER VISUAL STATUS INDICATOR (LED)

An optional LED tri-color visual status indicator mounted on the cabinet enclosure cover to provide information regarding DC output status.

KEY LOCK COVER

Optional key lock mounted on the cabinet enclosure cover available where tamper-resistance is required.

* See related products for backup batteries.

FIRE/EMERGENCY RELEASE INPUT

A fire alarm input provides simultaneous release of all fail safe locks and door holders in case of an emergency. An optional manual reset switch following a fire/emergency release or power loss is available to meet code compliance. When the optional manual reset feature is required, should an AC power loss occur or the emergency release input be actuated, personnel must restore secondary output power manually at the power supply after the emergency release signal is reset and/or AC power is restored.


SYSTEM ON/OFF SWITCHES

Optional System On/Off switches are available both inside the cabinet enclosure or on the cabinet enclosure cover.

DOOR CONTROL MODULES

Door control relay modules are available to meet virtually any application need. All wiring for lock hardware, access controls, remote controls and monitoring is terminated at one central location. Installation and troubleshooting is simplified. Modules may be factory installed or ordered separately for field installation as needed. Cabinet enclosures are pre-configured with mounting holes to accommodate door control modules. All modules are individually fused for protection of multiple station systems.

CROSS REFERENCE



	602	631	632	634	636
DC Output Rating	1 Amp	1.5 Amp	2 Amp	4 Amp	6 Amp
Small Cabinet	602RF	631RF	632RF	-----	-----
Large Cabinet	602RFA	631RFA	632RFA	634RFA	636RFA
Less Cabinet	602RFL	631RFL	632RFL	-----	-----
	CLICK TO VIEW	CLICK TO VIEW	CLICK TO VIEW	CLICK TO VIEW	CLICK TO VIEW



SPECIFICATIONS

634RFA

Input	115 VAC 1.2 Amp 50/60 Hz
Output	12/24 VDC (1) 4 Amp (2) 2 Amp Class 2
Battery Charger	13.5/27 VDC 500 mA
Cabinet	16" x 14" x 6½" 16 Gauge
Weight	25 lbs

BACKUP BATTERY DISCHARGE TIME

Standby Power	12 VDC			
Battery	RB12V7	RB12V7	RB12V7	RB12V7
Battery Qty*	1	2	3	4
Current Load	Power Backup Time (Hours)			
1 Amp	4.8	12.1	20.7	30.4
1.5 Amp	2.8	7	12.1	17.7
2 Amp	1.9	4.8	8.2	12
2.5 Amp	1.4	3.5	6.1	8.9
3 Amp	1.1	2.8	4.8	7
3.5 Amp	0.9	2.3	3.9	5.7
4 Amp	0.7	1.9	3.2	4.8

Standby Power	24 VDC**	
Battery	RB12V7	RB12V7
Battery Qty*	2	4
Current Load	Power Backup Time (Hours)	
1 Amp	4.8	12.1
1.5 Amp	2.8	7
2 Amp	1.9	4.8
2.5 Amp	1.4	3.5
3 Amp	1.1	2.8
3.5 Amp	0.9	2.3
4 Amp	0.7	1.9

[CLICK TO VIEW](#)

DOOR CONTROL MODULE CAPACITY***

Power Supply	634RFA	
Battery Qty*	0-2	3-6
VR	2	2
ACM	4	4
EMC	2	2
FB	4	4
UR1	4	4
CR	2	2
UR2	2	1
UR4	2	1
IPDC	1	-----
IPDS	1	-----

[CLICK TO VIEW](#)

* Battery quantity based on size of SDC's RB12V4 backup batteries.

** For 24 VDC standby power, minimum order of (2) batteries. Batteries must be ordered in pairs.

*** Total combined load of modules and access control hardware may not exceed power supply rating.



CERTIFICATIONS

UL 1012 Power Units Other Than Class 2

CSA-C22.2 No. 107.1 Power Conversion Equipment

UL 2043 Fire Test for Heat and Visible Smoke Release for Discrete Products and Their Accessories Installed in Air-Handling Spaces



HOW TO ORDER

FOLLOW STEPS FOR ORDERING

Designates optional step

1 SPECIFY MODEL														
634RFA 4 Amp DC Power Controller With Large Cabinet														
2 SPECIFY OPTIONS		4 SPECIFY BOARDS												
220 230 VAC, 50/60 Hz		VR Voltage Power Converter, 12VDC												
CL Cover Visual Status Indicator (LED)		ACM Six Input Control Relay												
KL Key Lock Cover		EMC Dual Channel Exit Device Sequencer												
MR Fire/Emergency Release Manual Reset Switch		FB Four Output Power Distribution Module												
3 SPECIFY ON/OFF		UR1 Microprocessor Controller, Two Relays												
PS1 Power On/Off Inside Cabinet Enclosure		CR Four Station Control Relay												
PS1A Power On/Off On Cabinet Enclosure Cover		UR2 Microprocessor Controller, Four Relays												
		UR4 Microprocessor Controller, Eight Relays												
		IPDC IPPro Controller, VR Included												
		IPDS IPPro Door Expansion, VR Included												
<table border="1"> <thead> <tr> <th>STEP NUMBER:</th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> </tr> </thead> <tbody> <tr> <td>ORDERING EXAMPLE:</td> <td>634RFA</td> <td>CL KL MR</td> <td>PS1A</td> <td>UR1 UR2</td> </tr> </tbody> </table>					STEP NUMBER:	1	2	3	4	ORDERING EXAMPLE:	634RFA	CL KL MR	PS1A	UR1 UR2
STEP NUMBER:	1	2	3	4										
ORDERING EXAMPLE:	634RFA	CL KL MR	PS1A	UR1 UR2										



RELATED PRODUCTS

BACKUP BATTERIES

SDC power supplies equipped with batteries provide continuous operation of access controls, locking devices and peripheral components during a power failure.

[CLICK TO VIEW](#)

RB12V7 12V/7Ah Battery

RB12V7-2 12V/7Ah Battery, Qty 2 Pack

