



INSTALLATION INSTRUCTIONS

491 EMERGENCY BREAK GLASS STATION

The SDC 491 "Break Glass" Emergency Door Release is ideal for immediate unlocking of perimeter doors or interior work area doors that are equipped with fail-safe electric locks. The SDC 491 is specifically designed for emergency door release and may influence the approval of an electric locking system.

This type of Emergency Door Release may be preferred over a pull station since greater commitment is required to break the glass.

FEATURES:

- Aluminum rod for striking the glass is included.
(Not required to break the glass.)
- Blue painted finish with easy to read Activation Instructions avoids confusion with red Fire Alarm stations.
- Includes (2) SPDT 10 Amp Contacts - 1 SPDT for Lock Release and 1 SPDT Auxiliary contact for Remote Monitoring, CCTV Activation or Alarm Activation.
- The SDC 491 may initiate the release of an individual door or multiple doors connected to an Electric Locking System.

OPTIONAL:

Back Box: Part No: 491-BB (5-1/4" x 3-1/4" x 1-1/2")

- The SDC 491 may be flush or recessed mounted in a 2" deep single gang box or double gang box with plaster ring cover. It may be surface mounted with an optional back box.

Replacement Glass Plates:

Part No: 491-GL4 (Qty. 4)

- Two replacement glass plates are included. If needed, additional replacement glass plates can be ordered.

DIMENSIONS:

5-1/2" x 3-1/2" x 1-3/8"

ELECTRICAL SPECIFICATIONS:

Switch Contacts: Dry (2) SPDT
10 Amp @ 30 VDC Resistive

Buzzer: 18mA max @ 24VDC

